

Tema Klampen 205 - LED module



Complete LED module for easy and efficient refurbishment of existing Tema Klampen 205 (Tema Klampen Lille). Not suitable for models delivered before 1996. See the compatible items below.

LED and driver specs:

LED type: Bridgelux Vero 10
 Energy consumption: 8 W
 Operational life: min 100,000 hours at ta max 25°C
 Colour temperature: 2700, 3000 or 4000 Kelvin
 Energy eff. class: F
 Colour rendering: min 90 Ra
 Colour accuracy: 3 Steps SDCM

Driver: 20 W LED driver, dimming optional
 Operational life: min 50,000 hours

Exchange of lamp module:

Remove housing and diffuser from the box by loosening the three bolts.

Remove lamp and ballast/condensator.

Insert the new LED module, connect leads and fasten the new LED module.

Mount the diffuser and the housing by means of the three bolts.

We include a blank label in the consignment. Write the old item number on the label and attach it inside the luminaire.



Variants

LED module for Tema Klampen 205				
Item No.	Lamp type	Select colour temperature and other options in the table below.		
1933-	8 W Bridgelux Vero 10, 250 mA			
Combine with:	Colour temperature	Dimming		
	927 2700 K, 90 Ra	V	1-10 V	
	930 3000 K, 90 Ra	D	Dali	
	940 4000 K, 90 Ra			
Example:	1933-930 = 8 W LED module, 3000 K, 90 Ra			
The above LED modules fit the following variants; X stands for colour code; old E-number in brackets:				
	6051X (49.43.331.900), 6161X (49.43.332.909), 6251X, 6851X			
	6051, 6850			